

Item 20118636

- Remote control panel for the power inverters (EG-PWC-PS pure sine series)
- The power switch and LED status indicators: DC input, AC output, load value, battery capacity, and possible fault state

SPECIFICATIONS

- Dimensions: 110 mm x 71 mm x 25 mm
- Net weight: 0.22 kg



WIRED REMOTE CONTROL PANEL FOR EG-PWC-PS POWER INVERTER SERIES

- VERKABELTES FERNBEDIENUNGSPANEL FÜR WECHSELRICHTER DER SERIE EG-PWC-PS
- BEKABELD AFSTANDSBEDIENINGSPANEEL VOOR DE EG-PWC-PS SERIE OMVORMERS
- PANNEAU DE COMMANDE À DISTANCE FILAIRE POUR LA SÉRIE D'ONDULEURS EG-PWC-PS
- ДРОТОВА ДИСТАНЦІЙНА ПАНЕЛЬ КЕРУВАННЯ ДЛЯ ІНВЕРТОРІВ ПОТУЖНОСТІ EG-PWC-PS
- KABELOVÝ DÁLKOVÝ OVLÁDACÍ PANEL PRO ŘADU VÝKONOVÝCH MĚNIČŮ EG-PWC-PS
- PRZEWODOWY PANEL ZDALNEGO STEROWANIA DO FALOWNIKÓW SERII EG-PWC-PS




GEMBIRD EUROPE B.V. <http://www.gembird.eu>
All brands and logos are registered trademarks of their respective owners

1 USING THE REMOTE CONTROL



NOTE: When using the remote control to turn the inverter on or off, please make sure the Main Switch on the inverter front panel is in the **OFF position**, or the remote-control main switch will not work.



connect

2 CONNECTING THE REMOTE CONTROL



+



3 REMOTE CONTROL PANEL

